

Diesel Generator Set:C100

Standard Features	
MODEL	C100
Standby Power(50Hz)	88KW/110KVA
Prime Power(50Hz)	80KW/100KVA
Engine	CUMMINS 6BT5.9-G2
Alternator	LEROYSOMER TAL-A44-D

- Standard control panel, Including controller, Operation lighting, Emergency stop button, Buzzer
- Main line circuit breaker
- Two 12V free maintenance battery, battery charger, Battery Ract and Battery Switch
- Industrial silencer, Ripple Flex exhaust pipe, Flange
- Fork lift position and lifting position
- With-10 hours Base Fuel Tank; Fuel Tank Capacity: 320L
- Radiator 50°C max, Fans driven by Belt, with safety Guard
- Hand pump special for take out dirty oil







Open Type

Silent Type

Generator Set Ratings						
Voltage	Frequency	Phase	P.F (COS ϕ)	Prime Current Amps	Standby Power (KW/KVA)	Prime Power (KW/KVA)
440/254	50	3	0.8	131	88/110	80/100
415/240	50	3	0.8	139	88/110	80/100
400/230	50	3	0.8	144	88/110	80/100
380/220	50	3	0.8	152	88/110	80/100

Prime Power(PRP):Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97(eqvISO8528);10% overload capability is available for a period of 1 hour within a 12-hour period of operation. Standby Power Rating (STP):The standby power rating is applicable for supplying emergency

Dimension & Weight Of Generator Set	
Dimension(L*W*H)/CM For Open Type	200×91×142 CM
Net Weight/KG For Open Type	1450 KG
Dimension(L*W*H)/CM For Silent Type	290×113×166 CM
Net Weight/KG For Silent Type	1900 KG
Dimension (L*W*H)/MM For Trailer Type	
Net Weight/KG For Trailer Type	



Specification of Engine		
Basic Specific ation	Engine Model	6BT3.9–G2
	Manufacturer	DCEC CUMMINS
	Prime Power	92KW/123HP
	Standby Power	100KW/134HP
	Engine Configuration	6Cylinder In Line, 4Stroke,Direct Injection
	Gas Feeding Model	Turbo Charged
	Bore×Stroke	102×120(MM)
	Displacement	5.9L
	Rated Speed	1500RPM
	Speed Governor	Electric Governor
	Starter Model	24V DC Start
	Cooling System	Water Cool
	Compression Ratio	17.5:1
Exhaust System	Exhaust Gas Flow	16.8M ³ /Min
	Exhaust Temperature	565℃
	Max Back Pressure	10kPa
Air Intake System	Max Intake Restriction	6.1kPa
	Burning Capacity	6.5M ³ /Min
	Air Flow	158M ³ /Min
Fuel System	Fuel Consumption (Prime Power 100%) Load	22L/H
	Fuel Consumption (Prime Power 75%) Load	17L/H
	Fuel Tank Capacity	320L
Lubricat ion System	Oil Capacity	16.4L
	Oil Consumption	≤4g/Kw.h
	Oil Pressure at Rated RPM	345kPa
Cooling System	Total Coolant Capacity	27L
	Thermostat Open Temperature	82-93℃
	Max Coolant Temperature	104℃

Specification of Alternator

Basic Specification	Alternator Model	TAL-A44-D
	Manufacturer	LEROYSOMER company
	Prime Output	80KW/100KVA
	Standby Output	88KW/110KVA
	Excitation Model	Brushless, Self-Exciting
	Cooling Method	Air Cooling
	Connection Type	3 Phase and 12 Wires "Star" Connection
	Power Factor	0.8
	Protection Class	IP23
	Insulation Class	H
	Altitude	≤1000m
	Voltage Regulation, Steady State	≤ ±1%
	Telephone Influence Factor	<50
	Sudden Voltage Warp (100% Sudden Reduce)	≤ ±1%
	Sudden Voltage Warp (Sudden Increase)	≤ ±25%
	Voltage Stable Time (100% Sudden Reduce)	≤6S
	Voltage Stable Time (Sudden Increase)	≤6S
	Frequency Reduce	0-5% adjustable
	Frequency Regulation, Stead State	≤1.5%
	Frequency Waving	≤0.8%
	Sudden Frequency Warp (100% Sudden Reduce)	≤+12%
	Sudden Frequency Warp (100% Sudden Increase)	≤-10%
	Frequency Recovery Time (100% Sudden Reduce)	≤5S
	Frequency Recovery Time (Sudden Increase)	≤5S
Compliance GB755,BS5000,VDE0530,NEMAMG1-22,IED34-1,CSA22.2 and AS1359 Stands		

Control Panel System

1.SINGLE SET GEN-SET CONTROLLER

SUM : They meet all possible requirements for AMF applications,including modem control,user configuration and full gen-set monitoring and protection. AMF models enable the combination of manual and remote start application with auto mains fail function.

KEY FEATURES:

1. High water Temperature Shutdown

2. Low Oil Pressure Shutdown

3. Over Speed Shutdown

4. Over Crank Shutdown

5. Function as Emergent Stop

6. Heated Display Option

7. Breaker Control Buttons on Front Fascia

8. Alternative Configuration (50Hz/60Hz)

9.Support ATS Function



a.DSE 6020KII



b.ComAp AMF 20

KEY FEATURES:

1. High Water Temperature Shutdown

2. Low Oil Pressure Shutdown

3. Over Speed Shutdown

4. Over Crank Shutdown

5. Function as Emergent Stop

6. With Remote Teleport Communication RS 485

7. Heated Display Option.

8. Alternative Configuration (50HZ/60HZ)

9. Support ATS Function

10. Remote Communications (RS232 & RS485)

11. Fuel Usage Monitor And Low Level Alarms.

12. Engine Specific J1939 for All Major Manufacturers

13. Configurable Display Languages.

14. Load Switching, Load Shedding&Dummy Load Outputs.

15. Alternative Configuration (50Hz/60Hz)



c.DSE 7320




d.ComAp AMF 25

2.Multiple PARALLELING GEN-SETS WITH INTERNAL LOAD-SHARING CONTROLLER

SUM: Functionality, optimized for ease of use, installation and configuration, includes built-in synchronization and digital isochronous active and reactive load sharer. Native co-operation of up to 32 gen-sets is a standard feature.

KEY FEATURES:

1. The Most up to 32-set Synchronization	
2. Wide Range of Communication Interfaces – RS232, RS485, USB, Modbus, GSM/Analog Modem, GPRS, Ethernet	
3. Direct Governor & AVR Control	
4. kW & kV Ar Load Sharing	
5. Advanced Power Management Function	
Load Dependent Start/Stop	
Load Demand Swap	
Running Hours Equalization	
6. Support of Electronic Controlled Engines (J1939, Modbus)	b.ComAp IC-NT NINT

3.SINGLE GEN-SET IN PARALLEL TO MAINS CONTROLLER

SUM: They are integrated controllers combining AMF and paralleling functions for single gen-sets. This combination allows the gen-set with interrupt-free transfers as well as in continuous parallel-to -mains mode.

KEY FEATURES:

1. Mains (Utility) Failure Detection, Mains (Utility) Power Monitoring (kW, kV Ar, kV A & pf) Monitoring, Mains (Utility) Decoupling Protection, Mains (utility) kW Export Protection.	
2. Remote Communications (RS232, RS485 x2, Ethernet)	
3. High Tariff Avoidance, Peak Shaving, Peak Lopping	
4. Synchronization of MCB (Reverse Synchronization)	
5. Support of Electronic Controlled Engines (J1939, Modbus)	b.ComAp IC-NT SPtM
6. Wide Range of Communication Interfaces – RS232, RS485, USB, Modbus, GSM/Analog Modem, GPRS, Ethernet	

Generator Set Options and Accessories			
Generator Set Design		Control System	
Open Type	☐	AMF(Automatic Management Function)	☐
Silent Type	☐	ATS(Automatic Transfer System)	☐
Super Silent Type	☐	ASS(Automatics Synchronization System)	☐
Trailer Type	☐	Remote Control Puma	☐
Fuel System		Alternator	
12 Hour Base Tank(single wall)	☐	PMG(EBS) Excitation	☐
24 Hour Base Tank(single wall)	☐	Space Heater	☐
Dual Wall Base Fuel Tank	☐	Preheater System	
Outside Fuel Tank	☐	Coolant Preheater	☐
Automatic Refueling Compensation System	☐	Oil Preheater	☐
Exhaust System		Battery Preheater	☐
Residential Exhaust Silencer	☐		
Circuit Breaker Brand			
CHNT	☐		
ABB	☐		